



General Settings For Internet & MMS

Network or Profile Name:	AirVoice Web or Mobile_WAP
WAP Homepage URL:	http://www.avmobileweb.com
Internet WAP APN or Access Name:	att.mvno
Internet Proxy or IP Address:	66.209.11.33
Proxy Port:	80 or 8080
User Name & Passwords:	leave blank - empty
Network or Profile Name:	AirVoice MMS or Mobile_MMS
MMS URL:	http://mmsc.cingular.com
MMS APN or Access Name:	att.mvno

For manual setup, make sure to create & setup new profiles for Browser Setting & Multimedia Message and set them as Default settings.

General Step By Step Settings

WAP Browser Settings:

1. Select Menu
2. Select Settings
3. Select Set Applications
4. Select Browser Settings
5. Select Profile Settings
6. Set Name: **Mobile_WAP**
7. Access Name: **att.mvno**
8. Auth. Type: **Normal**
9. User ID: **None**
10. Password: **None**
11. Protocol: **HTTP**
12. Home URL:
<http://www.avmobileweb.com>
13. Proxy Address: **66.209.11.33**
if there is no individual Proxy Port setting then make the Proxy Address: **66.209.11.33:80**
14. Proxy Port: **80**
15. Linger Time: **300 or default**
16. Select Advance Settings
17. Static IP: **Automatic - none**
18. Static DNS: **Automatic - none**
19. Traffic Class: **Subscribed - None**
20. **SAVE**

Browser Profile Selection:

1. Select Menu
2. Select Settings
3. Select Applications Settings
4. Select Browser
5. Select Browser Profiles
6. Select Mobile_WAP

MMS Settings:

1. Select Menu
2. Select Settings
3. Select Connectivity
4. Select Network Profiles
5. Select Create
6. Set Name: Mobile_MMS
7. Access Name: att.mvno
8. Auth. Type: Normal
9. User ID: None
10. Password: None
11. Protocol: HTTP
12. Home URL:
<http://mmsc.cingular.com>
13. Proxy Address: 66.209.11.33
if there is no individual Proxy Port setting then make the Proxy Address: 66.209.11.33:80
14. Proxy Port: 80
15. Linger Time: 300 or default
16. Select Advance Settings
17. Static IP: Automatic - none
18. Static DNS: Automatic - none
19. Traffic Class: Subscribed - None
- 20: SAVE

MMS Profile Selection:

1. Select Menu
2. Select Settings
3. Select Applications Settings
4. Select Messaging
5. Select Multimedia Messages
6. Select MMS Profiles
7. Select Mobile_MMS

OTA's Will Work With Most Of The Unlocked Handsets

OTA – Over The Air

Call customer service at (888)944-2355 and they will send an OTA with 2 messages to the phone, **Mobile_WAP** & **Mobile_MMS**. All you do is **download the 2 messages** and make them as default. The OTA message will ask for a **code – 1234** will be the code for all. Phone will automatically be setup to use Browsing and MMS.

There will actually be more than 2 messages sent to the phone because of the amount of characters each message can hold, each message will come in as multiple message explaining what the message is and how to download it by using code 1234

For locked AT&T handsets we can send an OTA to the following phones only at this time. We are working on trying to make all locked AT&T handsets to work with OTA.

Samsung Phones

867

877

887

237

167

177

LG Phones

LG GR500

LG CU920

**Samsung 767
Firmware Version
A767UCHI4 ONLY**